



63mm



Bells still remain a popular choice for many applications such as schools where they can sometimes be used as a signal for non fire purposes such as class change. All CF bells incorporate highly efficient rotary centrifugal movements combining high sound output with low current consumption.

- HIGH SOUND OUTPUT
- LOW CURRENT CONSUMPTION
- SIMPLE INSTALLATION
- MULTIFIXING BASEPLATE

Specification

Voltage	8-16Vdc 20-28Vdc
Current	222mA (typical) @ 12V 25mA (typical) @ 24V
Sound Output	93dB(A) 12V 95dB(A) 24V
Monitoring	Reverse polarity
Temperature	- 10°C to + 55°C
Protection	IP21C
Construction	Gong -Steel, Base - Polycarbonate
Weight	0.85Kg
Colours	Gong - Red Base - Black

